WWW.FANVIL.COM

# C400/C600

## Smart IP Phone C400/C600 Quick Installation Guide



VoIPon www.voipon.co.uk sales@voipon.co.uk Tel: +44 (0)1245 808195 Fax: +44 (0)1245 808299



Smart VolP



## Instruction



### C400/C600

Overview

### Included Accessories

Smart IP Phone C400/C600	Handset
Power adaptor	Handset cord
Quick Installation Guide	Ethernet Cable
Base bracket	



## Instruction



### C400/C600

Overview

### Included Accessories

Smart IP Phone C400/C600	4	Handset
Power adaptor	Q	Handset cord
Quick Installation Guide	9	Ethernet Cable
Base bracket		

Front view and keypad instruction:



Connect the IP Phone as shown by the following diagram:



VoIPon www.voipon.co.uk sales@voipon.co.uk Tel: +44 (0)1245 808195 Fax: +44 (0)1245 808299

## Configuration

#### Configuring via Web

- 1. Drag Status Bar on the top of Phone, and you would get the phone's network IP address.
- 2. Open web browser and input the IP with, such as http://192.168.1.1/ in the address bar. You would get ready to enter web interface and set up.
- \* The default Username / Password is "admin" / "admin".

← → C 前 ☆ http://***.***.*.*.**	Logon	× 🔁
	← → C f	t tp://***.***.€. ₹\$/
	f	
User:		User:
Passworu:		Passworu:
Logon	l	Logon

## Configuration

#### VoIP Settings

- 1. Selects SIP Line for registration
- 2. Input IP address, Server Port, Authentication User, Password, SIP User, and Display name... Enable "Mark", and Click "APPLY"

-anvil				
	SUP SUR			
BASIC	are cine last	1.21		
* NETWORK	Basic Settings >> Status	Registered	Domain Realm	_
	Server Address	172.18.1.2	Proxy Server Address	
> VOIP	Server Port	5060	Proxy Server Port	
and a second second	Authentication User	8810	Proxy User	
PHONE	Authentication Password	******	Proxy Password	
States and the second	SIP User	\$810	Backup Proxy Server Address	
FUNCTION KEY	Display Name	Adam	Backup Proxy Server Port	5060
	Enable Registration	1	Server Name	
MAINTENANCE				
Contraction and	Audio Codecs >>			
SECURITY	Advanced STP Settings>>			
and the second		tr.	terest of the second se	
LOCOUT		L	MERLY	

#### Configuring via LCD menu

#### Network Settings

- 1. Press "Phone Menu ICON" on the screen.
- 2. Select and Press "Network".
- 3. Select DHCP, Static IP, or PPPoE and "SAVE"
- \* The default value is DHCP. If you select Static IP or PPPoE, please input the necessary information follow by the screen.

#### VoIP Settings

- 1. Press "Phone Menu ICON" on the screen.
- 2. Select and Press "Accounts"
- 3. Please input MENU Password "123456" and Enter
- 4. Input Server address, Server port, Authentication User, Password and SIP User... Enable Registration "Mark", and Click "SAVE"

## 6 Make a Phone Call

### Make a call

- 1. Lift Handset, Dialing ICON, or SPEAKER Key
- 2. Select the SIP line you would like to use it
- 3. Dial the number Press "#" sign or Video ICON key(C600 Only) to make a Audio or Video Call
- \* If you have the wrong number need to delete it, please press ( to process it. Also, you can erase all of them by long pressing the delete ICON.

### Answer a call

- 1. Audio Call (Default Configuration) -- Lift Handset or Press the SPEAKER key
- Video Call (C600 Only)
  Pressing the Video ICON to answer it. Or you can Lift Handset or Press the SPEAKER key if the phone had pre-programmed Video as Default.
- \* You could see the contact's picture (pre-installed), name, and phone number when you receive a call which is in your contact list.
- \* You can switch the Audio to Video conversation if the other party accept your request by pressing the Video Request ICON.

### Call Transfer

- 1. During the conversation with Party A, press the "Transfer" key, make another call conversation with Party B and Pressing the "Transfer " Key again.
- 2. During the conversation with Party A, press the "Transfer" key, dial party B number than pressing the "Transfer" key again.

## Call Conference

During the conversation with Party A, press the "Conference" key, make another call conversation with Party B and pressing the "Conference" key again.

- \* During the three parties' conversation status, you can press either the picture of Party A or Party B to switch the individual conversation of each party.
- \* During the three parties' conversation status, you can skip the current conversation by pressing the "Exit". The other two parties can continue conversation without interrupting.



VolPon www.voipon.co.uk sales@voipon.co.uk Tel: +44 (0)1245 808195 Fax: +44 (0)1245 808299

Connect the IP Phone as shown by the following diagram:



VoIPon www.voipon.co.uk sales@voipon.co.uk Tel: +44 (0)1245 808195 Fax: +44 (0)1245 808299

## Configuration

#### Configuring via Web

- 1. Drag Status Bar on the top of Phone, and you would get the phone's network IP address.
- 2. Open web browser and input the IP with, such as http://192.168.1.1/ in the address bar. You would get ready to enter web interface and set up.
- \* The default Username / Password is "admin" / "admin".

← → C 前 ☆ http://***.***.*.*.**/
User:
Passworg:
Logon



VolPon www.voipon.co.uk sales@voipon.co.uk Tel: +44 (0)1245 808195 Fax: +44 (0)1245 808299