

### **Openvox V100-BOX-400(Up to 400 transcoding Sessions)**



Product Name: Openvox V100-BOX-400(Up to 400 transcoding Sessions) Manufacturer: -Model Number: -

Please Note: This product has been discontinued. For an alternative, please see the other OpenVox Transcoding Cards.

Openvox V100-BOX Up to 400 transcoding Sessions,Enclosure V100-BOX-400 The Openvox V100-BOX-400 is an integrated box designed to streamline installation,With an extern Power Supply, it can work alone by using Ethernet port and also being stacked up to 5 instances on a 19 inch rack mount.The V100-BOX from Openvox can be worked with Asterisk® and FreeSWITCH®. Feature

High density up to 400 transcoding Sessions
No addionnal License Fee1
Relieve Host CPU Load
Release API for Integration
OS : Linux and Windows
Integrates in Asterisk® and FreeSWITCH®
Support distributed or intergrated Application

Openvox V100-BOX-400 - Technical Specifications Codec Support

• G.711 • GSM-FR

• G.722 • GSM-EFR

• G.722.1 • AMR

• G.726 • AMR-WB (G.722.2)

• G.729AB • iLBC

\* Except for AMR and AMR-WB Target Applications

i¿½ Hosted VoIP GateWay i¿½ Conferencing Server



## Openvox V100-BOX-400(Up to 400 transcoding Sessions)

i¿½ IVR Server i¿½ Distributed Office PBX i¿½ Call Centers

Dimensions

� 131x67.5x31mm

Interface

ï¿1⁄2 10/100/1000 BASE-T RJ45

**Power Requirments** 

ï¿1∕2 0.6A @12V

**Operating Temperature Range** 

ï¿1/2 0 – 50 °C

Humidity

ï¿1/2 10 TO 90% NON-CONDENSING

Hardware And Software Requirement

ï¿1/2 Windows/Linux in Host

Certifications

ï¿1/2 FCC Part 15B,EN55022 Class B,EN55024 EN60950 (Pending)

Warranty

ï¿1/2 5-year warranty

**Related Accessories** 

The OpenVox V100-Bracket is a 1U & amp; 19" bracket, designed for rackmounting installation of up to 5 instances of V100-BOX.

#### **Please Enquire**

Options available for Openvox V100-BOX-400(Up to 400 transcoding Sessions) :

#### V100-Bracket Required?



# **Openvox V100-BOX-400(Up to 400 transcoding Sessions)**

Not Required, Required (+£35.00).