



Product Name: Yealink T41S IP Phone (SIP-T41S) Manufacturer: -Model Number: SIP-T41S

Please Note: This product has been discontinued. Please see the Yealink T42U IP Phone for an available alternative.

Yealink T41S IP Phone (SIP-T41S) The Yealink T41S is a feature-rich business tool for superior communications and extended functionality. The SIP-T41S is a six-line IP phone that comes with built-in programmable keys to enhance productivity. Yealink T41S Key Features

i¿½ Up to 6 SIP accounts
i¿½ 2.7" 192x64-pixel graphical LCD with backlight
i¿½ Opus\* codec support
i¿½ USB 2.0
i¿½ T4S Auto-P template unified
i¿½ T4S firmware unified
i¿½ PoE support
i¿½ Paperless label design
i¿½ Headset, EHS support
i¿½ Integrated stand with 2 adjustable angles

ï¿1∕2 Wall mountable

With an all-new USB port, the SIP-T41S boasts unparalleled functionality and expansibility, which comes ready for future Bluetooth, Wi-Fi and USB recording features. The new T4S series offers the same elegant appearance of the T4 line, but with improvements for greater interoperability and collaboration. The SIP-T41S features Yealink Optima HD Voice technology and wideband codec of Opus delivers superb audio quality and crystal clear voice communications. The T41S offers a faster, more-responsive interface than the T41P and several performance-enhancing functions.

Yealink T41S Technical Specification Audio Features

i¿½ HD voice: HD handset, HD speaker
i¿½ Hearing aid compatible (HAC) handset
i¿½ Wideband codec: Opus\*, G.722
i¿½ Narrowband codec: Opus\*, G.711(A/µ), G.723.1, G.729AB, G.726, iLBC
i¿½ DTMF: In-band, Out-of-band(RFC 2833) and SIP INFO
i¿½ Full-duplex hands-free speakerphone with AEC
i¿½ VAD, CNG, AEC, PLC, AJB, AGC

Phone Features

� 6 VoIP accounts

� One-touch speed dial, redial

ï¿1/2 Call forward, call waiting

ï¿1/2 Call transfer, call hold

ï¿1/2 Call return, group listening

ï¿1/2 Mute, auto answer, DND

ï¿1/2 3-way conference call

ï¿1/2 Direct IP call without SIP proxy



ï¿1/2 Ring tone selection/import/delete

ï¿1/2 Hotline, emergency call

ï¿1/2 Set date time manually or automatically

iزئ Dial Plan, XML Browser, Action URL/URI

� RTCP-XR (RFC3611), VQ-RTCPXR (RFC6035)

ïزائ USB port (2.0 compliant) Bluetooth earphone through BT40 (pending), Wi-Fi through WF40

(pending), USB call recording through USB flash drive (pending)

ï¿1/2 Enhanced DSS key

Directory

ï¿1/2 Local phonebook up to 1000 entries

� Black list

ï¿1/2 XML/LDAP remote phonebook

ï¿1/2 Smart dialing

ï¿1/2 Phonebook search/import/export

ï¿1/2 Call history: dialed/received/missed/forwarded

**IP-PBX** Features

- ï¿1/2 Busy Lamp Field (BLF)
- ï¿1/2 Bridged Line Apperance (BLA)
- ï¿1/2 Anonymous call, anonymous call rejection
- ï¿1/2 Hot-desking, voice mail
- ï¿1/2 Flexible seating
- ï¿1/2 Call park, call pickup
- ï¿1/2 Executive and Assistant
- ï¿1/2 Centralised call recording
- ï¿1/2 Visual voice mail
- ï¿1/2 Call recording

**Display and Indicator** 

ï¿1/2 2.7" 192x64-pixel graphical LCD with backlight

ï¿1/2 LED for call and message waiting indication

ïزئ Dual-colour (red or green) illuminated LEDs for line status information

 $\ddot{i}_{2}$  Intuitive user interface with icons and soft keys

ï¿1/2 Multilingual user interface

ï¿1/2 Caller ID with name and number

ï¿1∕₂ Power saving

Feature keys

ï¿1/2 6 line keys with LED

ïزئ 6 line keys can be programmed up to 15 paperless DSS keys (3-page view)

- ï¿1/2 5 features keys: message, headset, mute, redial, hands-free speakerphone
- ï¿1/2 4 context-sensitive "soft" keys

ï¿1/2 6 navigation keys

ï¿1/2 2 volume control keys

ï¿1/2 Illuminated mute key

ï¿1/2 Illuminated headset key

ï¿1/2 Illuminated hands-free speakerphone key

Interface



$$\label{eq:constraint} \begin{split} & \tilde{\imath}_{2}^{1/2} \ 2 \ x \ RJ45 \ 10/100M \ Ethernet \ ports \\ & \tilde{\imath}_{2}^{1/2} \ Power \ over \ Ethernet \ (IEEE \ 802.3af), \ Class \ 2 \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ USB \ port \ (2.0 \ compliant) \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ handset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \\ & \tilde{\imath}_{2}^{1/2} \ 1 \ x \ RJ9 \ (4P4C) \ headset \ port \ port \ headset \ port \ headset \ port \ port$$

**Other Physical Features** 

- ï¿1/2 Stand with 2 adjustable angles
- ï¿1/2 Wall mountable
- تزائر External Yealink AC adapter (optional):AC 100~240V input and DC 5V/1.2A output
- ï¿<sup>1</sup>/<sub>2</sub> Power consumption (PSU): 1.25-5.1W
- ï¿1/2 Power consumption (PoE): 1.72-6.73W
- ï¿1/2 Dimension (W\*D\*H\*T): 212mm\*189mm\*175mm\*54mm
- ï¿1/2 Operating humidity: 10~95%
- ï¿1/2 Operating temperature: -10~50°C

#### Management

- ï¿1/2 Configuration: browser/phone/auto-provision
- ïزئ Auto provision via FTP/TFTP/HTTP/HTTPS for mass deploy
- ï¿<sup>1</sup>∕₂ Auto-provision with PnP
- ï¿<sup>1</sup>/<sub>2</sub> Broadsoft device management
- ï¿1/2 Zero-sp-touch TR-069
- ï¿1/2 Phone lock for personal privacy protection
- ï¿1/2 Reset to factory, reboot
- ï¿1/2 Package tracing export, system log

Network and Security

ï¿1/2 SIP v1 (RFC2543), v2 (RFC3261) ï¿1/2 Call server redundancy supported ï¿1/2 NAT traversal: STUN mode ï¿1/2 Proxy mode and peer-to-peer SIP link mode ï¿1/2 IP assignment: static/DHCP ï¿1/2 HTTP/HTTPS web server ï¿1/2 Time and date synchronization using SNTP ï¿<sup>1</sup>/<sub>2</sub> UDP/TCP/DNS-SRV(RFC 3263) ï¿1/2 QoS: 802.1p/Q tagging (VLAN), Layer 3 ToS DSCP i¿1/2 SRTP for voice i¿1/2 Transport Layer Security (TLS) ï¿1/2 HTTPS certificate manager ï¿1/2 AES encryption for configuration file i¿1/2 Digest authentication using MD5/MD5-sess ï¿1/2 OpenVPN, IEEE802.1X � IPv6 ï¿1/2 LLDP/CDP/DHCP VLAN � ICE

Package Features

� Package content:- Yealink SIP-T41S IP phone- Handset with handset cord- Ethernet Cable (2m CAT5E UTP Cable)- Stand- Quick Start Guide- Power Adapter (Optional)- Wall Mount Bracket (Optional)



## **Please Enquire**

Options available for Yealink T41S IP Phone (SIP-T41S) :

## Power Supply Required?

None - Using PoE, UK PSU required (+£7.10).

RPS Extension ID

**RPS Extension Password** TEXT.

**RPS Display Name** TEXT.

RPS PBX URL TEXT.

RPS NAT Enabled TEXT. RPS Outbound Proxy TEXT.

RPS SIP Port TEXT.

**T4x Wall Mount Bracket** Not Required, Required (+£7.00).

### **Compatible Headsets**

JPL Connect-1 monaural headset and disconnect cord (+£65.20), Yealink UH36 Mono USB Headset (+£47.50), Yealink YHS33 IP Headset (+£35.10), Grandstream GUV3005 HD USB Headset with busy-light (+£68.00), JPLConnect-2 binaural headset and disconnect cord (+£76.25), Yealink UH36 Dual USB Headset (+£56.25), Not Required, Yealink UH33 USB Headset (+£24.00), Grandstream GUV3000 HD USB Headset (+£35.00).

### **Compatible Wireless Headsets**

Plantronics CS540 EHS Wireless headset and adapter (+£215.06), Not Required, Plantronics CS520 Binaural wireless EHS headset and adapter (+£260.89), Jabra Pro 920 Mono with remote handset lifter (+£137.80).

### **Headset Adapter**

Not Required, Yealink EHS36 (+£36.70).

Wi-Fi USB Dongle Required?

Not Required, Yealink WF50 Dual-Band WiFi Module (+£26.00).

### **DECT USB Dongle Required?**

Not Required, Yealink DECT USB Dongle DD10K (+£14.60).

## **Bluetooth USB Dongle Required?**

Not Required, Yealink BT41 Bluetooth USB Dongle (+£20.00).