

CHATAttach™ 170 | CHAT® 170

OPTIMIZED FOR
Microsoft®
Office Communicator

Personal/Group Speaker Phones for Microsoft Communicator 2007

Speaker phones for individual, small, medium or large group use, the CHATAttach 170 and CHAT 170 connect to PCs and laptops for rich, full-duplex audio communication with Microsoft Office Communicator 2007. The CHATAttach 170 and CHAT 170 are the perfect addition to the office or conference room for greatly enhanced collaboration.

ClearOne®



DELIVERS SUPERIOR
HANDS-FREE AUDIO
FOR MS OFFICE
COMMUNICATOR 2007

APPLICATIONS

Office Communicator 2007

Perfect for:

- + Boardrooms
- + Small, medium or large Conference Rooms
- + Executive Offices
- + Home Offices
- + Ad-hoc conferences any time, any place

ADVANTAGES

Provides high quality speakerphone capabilities on PCs or laptops:

- + Connect the CHATAttach 170 or the CHAT 170 to PCs and laptops via USB for hands-free, full-duplex audio with Office Communicator 2007
- + Incoming calls ring on the CHATAttach 170 and the CHAT 170
- + True plug-and-play operation
 - > Requires no drivers or software to be installed
- + Also provides crystal-clear audio for video conferencing and streamed multimedia content
- + Eliminates the need for large, expensive tabletop conference phones in executive offices
- + Replaces the PC's speakers and microphone with a high-quality, hands-free audio solution
- + Sleek industrial design complements the professional environment of boardrooms and executive offices

Enjoy crisp, clear audio:

- + Advanced ClearOne audio processing technologies deliver remarkably rich, full audio for natural, effortless conversations:
 - > True full-duplex performance allows users to listen and speak at the same time without audio cutting in and out
 - > Distributed Echo Cancellation® eliminates acoustic echo
 - > Noise cancellation identifies and removes ambient room noise
 - > Advanced automatic level management automatically adjusts microphone levels
- + Three built-in microphones provide full 360-degree coverage up to 8 feet from device
 - > Easily manage 1-6 call participants
 - > Provides rich audio from the far side participants
- + Full bandwidth frequency response delivers better audio

HDCConference™

> **CHAT 170 COMPONENTS**



CHAT 170 Unit
Part # 910-156-250



USB 2.0 Connection Cable
Part # 830-156-200



Quick Start Guide
Part # 800-156-253

> **CHATAttach 170 COMPONENTS**



Two CHAT 170 Units
Part # 910-156-250



USB 2.0 Connection Cable
Part # 830-156-200



CHATAttach Cable
Part # 830-156-010L



CHATAttach Power Supply
Part # 551-156-200




CHATAttach Quick Start Guide
Part # 800-156-225

Ready to use out of the box


All the components you need to quickly get up and running, including cabling and Quick Start Guide.

> **ROOM APPLICATIONS**

CHAT 170



CHATAttach 170



Configuration Software

Allows users to easily switch between devices; software applies optimized settings to CHAT 170 for each device. Auto-updates from the Web to keep software & CHAT 170 up-to-date with the latest enhancements.

> **SPECIFICATIONS**

Connections

USB Connector
Version 2.0 Compatible
Type: Mini B Female

Controls

Volume Up
Volume Down
Microphone Mute

Operating System Support

Windows XP
Windows Vista
Windows 7

Audio

Speaker Bandwidth: 190Hz - 20kHz
Max Output Level: 85dB SPL @ 1 meter

Microphone

Bandwidth: 100Hz - 12kHz

Processing

Full-duplex
Acoustic Echo Cancellation
Noise Cancellation
Automatic Level Controls

Power

USB-powered
5 VDC @ 500mA Maximum

Environmental

Operating Temperature: 5-40° C
(41-104° F)
Storage temperature: 0-70° C
(32-158° F)

Mechanical

CHAT 170 Dimensions (WxDxH):
7.4" x 7.4" x 1.8" (18.8cm x 18.8cm x 4.6cm)

CHAT 170 Weight:
1.17 lbs (.53kg)

Compliance

RoHS
FCC Class A Part 15
ICES-003
EU Compliance

Model Numbers

910-156-250

Chat 170

- Single CHAT 170 and Connecting Cable

910-156-250-00

CHATAttach 170

- Two (2) CHAT 170 Devices, Connecting Cables and Power Supply

Accessory Part Number

910-156-225

CHATAttach 160 Expansion Kit

- Includes Cables, Power Supply and Quick Start Guide to Update Two (2) CHAT 170 Devices to CHATAttach

> **CLEARONE LOCATIONS**