

OpenVox V100-ETH-400 Transcoding Card (Up to 400 transcoding Sessions)



Product Name: OpenVox V100-ETH-400 Transcoding Card (Up to 400 transcoding Sessions)

Manufacturer: -

Model Number: V100-ETH-400

Please Note: This product has been discontinued. For an alternative, please our other Asterisk Software.

OpenVox V100-ETH Up to 400 transcoding Sessions, Ethernet Card V100-ETH-400
The OpenVox V100-ETH-400 new generation transcoding card.

- Up to 400 transcoding sessions
- No Licensing Fees*
- PMC / Enclosure / Extending Evaluation Board / Ethernet card
- Reduce Host CPU Load
- Flexible Adaptability
- Provides RJ45 media/control flow paths.
- Works with Asterisk® and FreeSWITCH®;

Because of its low bandwidth requirements, the voice data compression codecs, such as G.729, G.726, AMR, G.722, iLBC, etc., are commonly used in VoIP applications. The G.711 codec is commonly used in legacy telephone network. For bridging TDM to VoIP connectivity, it needs codec transformation. Compared with transformation in software, the V100, based Multicore-DSP, can convert more sessions of transcoding, reduce host CPU load. The V100-ETH does not need standard PCI Slot, and ATX 12V power supply is acceptable. The V100-ETH-400 can be worked with Asterisk® and FreeSWITCH®;

- No addionnal License Fee#65297;
- Relieve Host CPU Load
- Release API for Integration
- OS : Linux and Windows
- Integrates in Asterisk® and FreeSWITCH®;
- Support distributed or integrated Application

OpenVox V100-ETH-400 - Technical Specifications
Codec Support

• G.711
• GSM-FR

• G.722
• GSM-EFR

• G.722.1
• AMR

• G.726

OpenVox V100-ETH-400 Transcoding Card (Up to 400 transcoding Sessions)

• AMR-WB (G.722.2)

• G.729AB
• iLBC

* Except for AMR and AMR-WB
Target Applications

½ Hosted VoIP GateWay
½ Conferencing Server
½ IVR Server
½ Distributed Office PBX
½ Call Centers

Dimensions

½ 124.0x51.1mm (PCB)

Interface

½ 10/100/1000 BASE-T RJ45
½ UART

Power Requirements

½ 0.6A @ ATX12V

Operating Temperature Range

½ 0 – 50 °C

Humidity

½ 10 TO 90% NON-CONDENSING

Hardware And Software Requirement

½ Windows/Linux in Host

Certifications

½ FCC Part 15B，EN55022 Class B，EN55024 EN60950 (Pending)

Warranty

½ 5-year warranty

Please Enquire

OpenVox V100-ETH-400 Transcoding Card (Up to 400 transcoding Sessions)
