

JPL 611 VoIP Headset (575-121-001)

6]
T	

Product Name: JPL 611 VoIP Headset (575-121-001) Manufacturer: JPL Telecom Model Number: 575-121-001

JPL 611 VoIP Headset (JPL-611-PM)

The JPL JPL-611-PM is a stylish mid-office and contact centre headset suitable for regular phone users. The JPL-611-PM has a slim, flexible microphone boom arm and features Surround Shield noise cancellation. JPL 611 Key Features

- ï¿1/2 Single and dual ear options available
- ï¿1/2 Left / right ear side compatible
- $\ddot{\iota}_{2}^{1/2}$ Wideband enabled speakers
- ï¿1/2 Noise cancelling microphone
- ï¿1/2 Supplied with quick disconnect system(QD) QD compatible with Plantronics
- i¿1⁄2 'Put and stay' ratchet microphone boom arm
- ï¿1/2 Mid-weight headset, ~ 62g / ~94g
- ï¿1/2 Leatherette & amp; foam ear cushions included
- ï¿1/2 Sure-fit fully adjustable headband
- ï¿1/2 Headset bag & amp; hanging hook included
- ï¿1/2 Clothing clip, headset hook & amp; headset bag included
- ï¿1/2 Compatible with all known office phones
- ï¿¹/₂ Full range of bottom leads available
- ï¿1/2 12 Month repair or replacement warranty

JPL 611 Technical Specifications Microphone

- ï¿1/2 Impedance: Max. 2.2KΩ
- ï¿1/2 Sensitivity: -36dB ± 2dB at 1kHz
- ï¿1/2 Directivity: Noise Cancelling
- ï¿1/2 FrequencyRange: 200Hz~5000Hz
- ï¿1/2 Distortion: Less than 3%
- ï¿1/2 Power Supply: 3V DC
- ï¿1/2 S/N Ratio: More than 58dB

Speaker

- ï¿1/2 Impedance: 150Ω
- ï¿1/2 Sensitivity: 92 ± 3dB at 1kHz 60mV Input
- ï¿1⁄2 Max Input Power: 100mV
- ï¿1/2 Frequency Range: 300Hz~5000Hz
- ï¿¹/₂ Distortion: Less 3% at 1kHz 60mV

Price: £72.30

Options available for JPL 611 VoIP Headset (575-121-001) :

Disconnect Cord Required?

BL04-P (Grandstream, Yealink, Snom, Sangoma) (+£5.45),



JPL 611 VoIP Headset (575-121-001)

(+£24.00).

Not Required, BL01-P (Fanvil) (+£5.45), BL-054MS-P